Energy Saving Lamp

LogiLight®

www.logilight.org

Art No. EM0003

Energy Cost Meter "Premium"

100% Keep an eye on your energy consumption and energy costs; this way, you can reveal hidden "power guzzlers"; measures the power consumption of the connected device using your individual power tariff to calculate our energy costs when the device is switched on and when it is standby mode. By replacing these devices energy-saving devices, you can lower your power consumption and save money. Displays watts/volts/amperes/hertz, total power consumption, total cost, AC power. Can save cost, tariffs and power consumption.

Technical Specification:
- Normal operation voltage: 230Vac/50Hz 240Vac/50Hz
- Load current: Max. 16A
- Voltage working range: 175Vac ~ 276Vac
- Timing display range: 0 second ~ 9999 days
- Power display range: 0.001W ~ 9999W
- Voltage display range: 0.000 ~ 9999V
- Current display range: 0.000 ~ 9999A
- Frequency display range: 0.000 ~ 9999Hz
- Rate of electricity range: 0.000 ~ 99.99COST/KWH
- Total cost consumption range : $0.000 ~ 9999K
- Total energy consumption range: 0.000 ~ 9999KWH

Working Condition:
- Voltage:175Vac~276Vac
- Voltage frequency:45~65HZ
- Current:≤16A
- Temperature:-10~50°C

Packaging Information:
- Packing Dimension: mm
- Packing Weight: kg
- Carton Dimension: mm
- Carton Q'ty: pcs
- Carton Weight: kg

* The specifications and pictures are subject to change without notice.
*All trade names referenced are the registered namework of their respective owners.

RoHS compliant

EM0003
4 052792 031089

Made in China